

CO-CJX2-D

Contactors AC

Application

CJX2 AC contactor D series (hereinafter referred to as contactor) is mainly used circuits of AC50Hz(or 60Hz), voltage up to 660V, and current up to 95A, for long-distance switching on/off the circuits and frequent start-up and control of AC motor, and it can be combined with appropriate thermal relay to constitute electromagnetic starter, in order to protect circuits that may subject to operating overload.

Main Technical Data



CJX2-D09,12



CJX2-D18



CJX2-D25



CJX2-D32



CJX2-D40,50,65,80,95

Type	CJX2 -D09	CJX2 -D12	CJX2 -D18	CJX2 -D25	CJX2 -D32	CJX2 -D40	CJX2 -D50	CJX2 -D63	CJX2 -D80	CJX2 -D95
Rated Insulation	660	660	660	660	660	660	660	660	660	660
Conventional Thermal Current	20	25	32	40	50	60	75	80	110	125
Rated Operational Current 380V/AC3	9	12	18	25	32	40	50	63	80	95
Power of Controlled (kW)	2.2	3	4	5.5		11	15	18.5	22	25
	4	5.5	7.5	11		18.5	22	30	37	45
	4	5.5	9	11		22	25	37	45	45
	4	5.5	9	11		22	30	37	45	45
Installation	1. Two screw mounted 2. Din mounted (35mm)					1. Three screw mounted 2. Din mounted (35mm / 75mm)				

CO-CJX2-F

Contactor AC

Application

CJX2 AC contactor F series is mainly used circuits of AC50Hz(or 60Hz). With special coil,F series contactor can be used in 40-400Hz, voltage up to 600V, current up to 630A, for switching on/off the main circuits and frequent start-up and control of AC motor, and it can be combined with appropriate thermal relay to constitute electromagnetic starter, in order to protect circuits that may subject to operating overload.



CJX2-F115



CJX2-F150



CJX2-F225



CJX2-F780

Main Technical Data

Items	Model		CJX2-F 115	CJX2-F 150	CJX2-F 185	CJX2-F 225	CJX2-F 265	CJX2-F 330
Pole			3 / 4	3 / 4	3 / 4	3 / 4	3 / 4	3 / 4
Rated conventional heating current (A) AC-1			200	200	275	280	350	360
Rated operational current(A)	380/400V	AC-3	115	150	185	225	265	330
		AC-4	50	65	75	85	100	124
	660/690V	AC-3	70	90	108	115	170	190
		AC-4	25	32	38	40	47	60
Rated insulation voltage(V AC)			690	690	690	690	690	690
Power of controlled 3-phase cage motor(AC-3)	kW	380/415V AC	55	75	90	110	132	160
		660/690V AC	80	100	110	140	160	220
AC coil (V)			110,127,220,240,380,415,440,480,500,600					
Items	Model		CJX2-F 400	CJX2-F 500	CJX2-F 630	CJX2-F 800	CJX2-F 780	CJX2-F 1000
Pole			3 / 4	3 / 4	3 / 4	3 / 4	3 / 4	3 / 4
Rated conventional heating current (A) AC-1			430	580	850	850	1200	1200
Rated operational current(A)	380/400V	AC-3	400	500	630	800	780	1000
		AC-4	150	185	188	195	240	-
	660/690V	AC-3	235	290	360	486	-	-
		AC-4	72	85	170	-	-	-
Rated insulation voltage(V AC)			690	690	690	690	690	690
Power of controlled 3-phase cage motor(AC-3)	kW	380/415V AC	200	250	335	400	400	500
		660/690V AC	280	330	450	475	475	670
AC coil (V)			110,127,220,240,380,415,440,480,500,600					