

PILOT LIGHT

AD16-22

Application

The product is mainly used in the circuits of AC 50Hz/60Hz, rated voltage up to 380V. It is applied into telecommunications, electrical and other lines for indicating signals, warning signals, accident signals and other indicative signals.

Technical Data

| | |
|--------------|--------------------------------|
| Model No. | AD16-22D/S |
| Material | LED lamp with ABS cover |
| Voltage | 12V,24V,36V,48V,110V,220V,380V |
| Frequency | AC50~60Hz |
| Rated Power | 10W |
| Insulation | $\geq 2M\Omega$ |
| Brightness | $\geq 100cd/m^2$ |
| Applicable | -25°C~+50°C |
| Installation | Screw installation |



Dimension

