

CONTACTOR AUX-F4 series



APPLICATION / DESCRIPTION

The F4 series auxiliary contact is a supporting accessory for JZC4 and CJX2 series products, which can be combined into delay contactor, reversible contactor and Star-delta starters by adding different functions.

F4 series auxiliary contacts can be installed on the top of JZC4 series contact relay. As a means to expand the number of contacts, the auxiliary contact group adopts the sliding friction contact contact function to ensure reliable circuit connection. F4 series auxiliary contacts consist of 8 specifications, F4-11, 20, 13, 31, 22, etc.

| TYPE | F4-11 | F4-20 | F4-02 | F4-13 | F4-31 | F4-22 | F4-40 | F4-04 |
|---------------|-------|-------|-------|-------|-------|-------|-------|-------|
| The NO. of NO | 1 | 2 | 0 | 1 | 3 | 2 | 4 | 0 |
| The NO. Of NC | 1 | 0 | 2 | 3 | 1 | 2 | 0 | 4 |

PART NUMBER EXAMPLE

| BASE NUMBER | The NO. of NO | The NO. Of NC |
|----------------|--|---------------|
| CO-AUX-F4 | 2 | 2 |
| EXAMPLE | CC-AUX-F4-22 (CONTACTOR AUX F4-22 2NO+2NC) | |

MAIN TECHNICAL DATA

| | | |
|--|-----------|---------------------------------|
| Rated insulation voltage V | | 660 |
| Resistive current Ith A | | 10 |
| Minimum load (reliable operation) | | 6V×10mA |
| Rated control power | DC | DC-11 220V 33W / DC-13 50W |
| | AC | AC-11 380V 300VA / AC-15 400VA |
| Electric life | | 120 x 10 ⁴ |
| Mechanical life | | 1000 x 10 ⁴ |
| Frequency of operation h-1 | | 3000 |
| Coil Voltage VAC | | 24, (36), 18, 110,(127),220,380 |